



Product Code: CL053

Luckinslive 397908132

Description: 13A Fused Connection Unit With Neon & Optional Flex Outlet



**General Information**

|  |   |   |
|--|---|---|
| Dimensions (mm)                        | 80 (W) x 80 (H) x 42 (D)  |   |
| Plate Fixing Centres - Horizontal (mm) | 60.3  |   |
| Style                                  | Metal Clad  |   |
| Colour                                 | Grey  |   |
| Materials                              | Front Plate & Mounting Box:<br>Electrophoretically Coated Steel | Insert, Fuse Drawer & Housing: Urea     |
|  | Neon Lens: Polycarbonate  | Terminals: Brass                        |
|  | Terminal Screws: Steel & Yellow Passivated                      | Internal Busbars: Formed Pressed Brass  |
|  | Earth Strap: Mild Steel   |   |
| Operating Voltage (AC)                 | 250   | Frequency (Hz) 50                       |
| Resistive Load Rating (A)              | 13  |   |
| Fuse Fitted Type                       | Plug Top Cartridge Fuse   |   |
| Termination Type                       | Screw   |   |
| Terminal Size (mm)                     | Ø5  | Terminal Torque Value (Nm) 2            |
| Terminal Capacity - Solid (mm²)        | 3 x 2.5 or 2 x 4  |   |
| Switched                               | No  |   |
| Twin Earth Terminals                   | Yes   |   |
| Neon Indicator                         | Yes   | Indicator Colour Red                    |
| Flex Outlet Available                  | Yes   |   |
| Flex Outlet Location                   | Front of Plate  | Flex Outlet Dimension (mm) Ø10          |
| Supplied Back Box Depth (mm)           | 40  |   |
| Back Box Knockouts - Total (mm)        | 5 x Ø20   |   |
| Back Box Knockouts - Top (mm)          | 2 x Ø20   | Back Box Knockouts - Sides (mm) 1 x Ø20 |
| Back Box Knockouts - Bottom (mm)       | 1 x Ø20   | Back Box Knockouts - Rear (mm) None     |
| Back Box Earth Terminal Supplied       | Yes   |   |
| Ingress Protection                     | IP20  |   |
| Operational Temperature (°C)           | -5 to +40   |   |
| Warranty (Years)                       | 20  |   |

**Standards** BS 1363-4, BS 1362

**Additional Information**

For cleaning / polishing of products, use only a soft, dry, clean cloth.  
 Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.  
 Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.



Catalogue



Range



DoC



Installation

